

# Wireless Tuner

## 2-Channel Diversity UHF Wireless Tuner



### Features

- 16 selectable channel frequencies
- Antenna cascade output function (parallel connection possible for linking two units)
- Auto mixing input function
- Tuner unit connections accessible from the front (even if rack mounted, the front panel is easily opened)
- Mix output/tuner 1 output (selectable), tuner 2 has 2 outputs
- Whip antenna x 2
- Compact 19" rack-mount design
- External antenna input (A/B)

### Specifications

Power Requirement	12 – 18 V DC
Power Consumption	250 mA (12 V DC when operating with two tuner modules)
Receiving Frequency	576 - 865 MHz* <sup>1</sup> , UHF
Channel Selectable	16 CH
Mixing Input	-20 dB* <sup>2</sup> , 10 k $\Omega$ , unbalanced, phone jack
Antenna Input	75 $\Omega$ , BNC (phantom powering for antenna) 9 V DC, 30 mA (max.)
Antenna Output	75 $\Omega$ , BNC (Gain 0dB)
Indicator	ANT A/B, Audio (peak), Power
S/N Ratio	Over 102dB (A-weight, unbalanced output)
Harmonic Distortion	Under 1%
Frequency Response	50 – 18,000 Hz, $\pm 3$ dB
Operating Temperature	-10°C to +50°C (14°F to 122°F)
Finish	Resin, black
Dimensions	210(W) $\times$ 44(H) $\times$ 181(D) mm (8.27" $\times$ 1.73" $\times$ 7.13")
Weight	770 g (1.70 lb) (without tuner module)
Accessory	Rod antenna $\times$ 2, Rubber foot $\times$ 4
Option	Rack mounting Kit